

HDMI 3/5/8 PORTS SWITCH SERIES

3/5/8 Ports High Definition HDMI Switch

Description

When you have multi HDMI signal source, no need to plug and unplug the HDMI cable, from the one HDMI device to another, with this 3/5/8 port HDMI switch, the problem will be solved. You can make the switch via the buttons on the panel, buttons on the Ir remote controller, and intelligent switch, to choose the 3/5/8 port HDMI or DVI signal source, output to one terminal display device. The HDMI switch can switch multi video and audio simultaneously. The high definition mode can be up to 720P, 1080i, 1080P, 4K*2K. It will maximize your home theatre and make it to be the best.

Product Picture



Specifications

Model	JHS10/3X1/AUTO	JHS11/5X1/AUTO	JHS12/8X1/AUTO
HDMI Signals	3	5	8
HDMI outputs	1		
HDMI input interface	19PIN HDMI		
HDMI output interface	19PIN HDMI		
HDCP	Compatible		
LED and Indicators	3	5/Digital Screen	8/Digital Screen
Resolution	4K*2K@30Hz		
Data Speed	3.4Gbps		
Switch Mode	Button, Ir Remote Controller, Intelligent Switch		
Ir Switch Mode	Support		
Ir Distance	<10 meters		
Ir Button Value	1,2,3	1,2,3,4,5	1,2,3,4,5,6,7,8,9,0
Working Voltage	DC5V		
Operation Temperature	0~70°C		
Storage Temperature	0~50°C		
Storage Humidity	90% without condensation		
Power adapter	DC5V@1000mA DC5V@1000mA DC5V@1000mA		
Shell	Metal		
Product Dimension(mm)	178*67*22	270*135*25	440*150*40
G.W.	0.41Kg	0.98Kg	1.3Kg
Packaging(mm)	220*150*50	300*220*55	550*230*120
Engineering/Multimedia/Test Zone			

Features

- Compatible with HDMI and DVI and high definition TV with HDCP.
- Backward compatible with DVI.
- Each input port support HDMI and DVI input.
- Differential interface support differential (TMDS) signal input.
- Support high resolution input 720P, 1080i, 1080P,4K*2K.
- Support video and audio format.
- Support signal speed up to 3.4Gbps.
- Support high definition signal transmission without any loss.
- Plug and play, no need for any extra software.
- Easy installation, connect 3/8/16 port signal source to high definition device.
- Multi switch method available:Button on the panel, IR Controller, Smart selction and so on.